

Specification Approval Sheet

Name: Nickel-Metal Hydride Battery

Model: 10003

SPEC: 8.4V (9V size) 200mAh LSD Cell

File Number:/

Project: /

Approved By	Checkup	Make
Andy	/	Haixia Bi
2016-7-13	/	2016-7-13

	Signature	Date
Customer	Company Name:	
Confirmation	Stamp :	

436 Kato Terrace, Fremont, CA 94539 U.S.A. Tel: 510.687.0388 Fax: 510.687.0328

www.Tenergv.com





Fremont, CA 94539

Tel: 510.687.0388 Fax: 510.687.0328 www.Tenergy.com email: sales@tenergy.com

Amendment Records

Description	Issued Date	Approved By
New release	2016-5-23	Haixia Bi
Update the battery performance parameters	2016-7-13	Haixia Bi
	New release	New release 2016-5-23

Tenergy Corporation



436 Kato Terrace Fremont, CA 94539 388 Fax: 510.687.0328

Tel: 510.687.0388 Fax: 510.687.0328 www.Tenergy.com email: sales@tenergy.com

1 Scope

This document describes the performance characteristics and testing methods for Nickel-Metal Hydride battery produced by Tenergy Corporation.

2 Product type and model number

2.1 Product type

Nickel-Metal Hydride Battery

3 Rated performance

Form 1: Battery rated performance

No	Item	Rated performance	Remark
1	Rated capacity	Nominal 200mAh Min 200mAh-5%	Standard discharge after standard charge
2	Nominal voltage	8.4V	Mean operation voltage during standard discharge after standard charge
3	Voltage at end of discharge	7V	Discharge cut-off voltage
4	Charging voltage	10.5V	
5	Impedance	≤750 mΩ	
6	Standard charge	Constant current 0.1 C_5A Constant voltage 10.5V Cut-off current \leq 0.03 C_5A	
7	Standard discharge	Constant current 0.2 C ₅ A End voltage7V	
8	Fast charge	Constant current 0.5C ₅ A Constant voltage10.5V Cut-off current ≤0.03C ₅ A	
9	Fast discharge	Constant current 0.5 C ₅ A End voltage7V	
10	Maximum continuous discharge current	2C	
11	Operation temperature range	Charge: 0~45°C	65±20%R.H
11		Discharge: -20~50°C	0.5±20%K.H
12	Cycle life	>500cycles	IEC61951-2(2003)7.4.1.1
	Storage temperature	≤1 month: -20 ~ 60°C	
13		≤3 months: -20 ~ 40°C	65±20%R.H, Best 10~25°C for long-time storage
		≤1 year:20 ~ 30°C	Best 10 25 c for long time storage
14	Weight	Approx: ≈36g	
15	Dimension(mm)	Thickness*Width*Height(Max)	16.5*26*48mm
16	output wire length (mm)	Excluding the connector	/±5mm

436 Kato Terrace Fremont, CA 94539

Tel: 510.687.0388 Fax: 510.687.0328 www.Tenergy.com email: sales@tenergy.com

4 Electrical performances

Form 2: Battery electrical performances

Table 5-Endurance in cycles

No	Items	Test procedure	Requirements
1	Nominal voltage	The average value of the working voltage during the whole discharge process.	8.4V
2	Discharge performance	The discharge capacity of the battery, measured with 0.2 C_5A down to 7V within 1 hour after a standard charge at $25\pm5^{\circ}C$	Discharge ≥Minimum capacity
3	Capacity retention	Standard charge, storage for 28 days, standard discharge at $45^{\circ}\mathrm{C}$	≥80%
		Standard charge, storage for 1 year, standard discharge at 20°C	≥80%
4	Cycle life	IEC61951-2(2003)/7.4.1.1	>500cycles

Notes: IEC61951-2(2003)/7.4.1.1 Cycle Life Test:

Cycle number	Charge	stand in Charged condition	Discharge
1	0.1 C5A,16h	none	0.25 C5A ,2h 20min
2—48	0.25 C5A, 3h10min	none	0.25 C5A ,2h 20min
49	0.25 C5A, 3h10min	none	0.25 C5A to 1.0V/cell
50	0.1 C5A,16h	1h-4h	0.2 C5A to 1.0V/cell
Cycle 1 to 50 shall be repeated until the discharges duration on any 50th cycle becomes less than 3hrs			

5 Standard test conditions

Test should be conducted with new batteries within one week after shipment from our factory and the batteries shall not be cycled more than five times before the test. Unless otherwise defined, test and measurement shall be done under temperature of $20\pm5^{\circ}$ C and relative humidity of $45\sim85\%$. If it is judged that the test results are not affected by such conditions, the tests may be conducted at temperature $15\sim30^{\circ}$ C and humidity $25\sim85\%$ RH.

6 Cautions in use

To ensure proper use of the battery please read the manual carefully before using it.

6.1 Handling

Do not expose to, dispose of the battery in fire.

Do not put the battery in a charger or equipment with wrong terminals connected.

Avoid shorting the battery.

Avoid excessive physical shock or vibration.

Tenergy Corporation



436 Kato Terrace Fremont, CA 94539

Tel: 510.687.0388 Fax: 510.687.0328 www.Tenergy.com email: sales@tenergy.com

Do not disassemble or deform the battery.

Do not immerse in water.

Do not use the battery mixed with other different make, type, or model batteries.

Keep out of the reach of children.

6.2 Charge and discharge

Battery must be charged in appropriate charger only.

Never use a modified or damaged charger.

Do not leave battery in charge over 24 hours.

6.3 Storage

Store the battery in a cool, dry and well-ventilated area.

6.4 Disposal

Regulations vary for different countries, Dispose of in accordance with local regulations.

7 Battery operation instruction

7.1 Charging

Charging current: Cannot surpass the biggest charging current which in this specification book stipulated.

Charging voltage: Does not have to surpass the highest amount which in this specification book stipulated to decide the voltage.

Charging temperature: The battery must charge in the ambient temperature scope which this specification book stipulated. Use the constant electric current and constant voltage to charge. Do not reverse charge. When the positive electrode and the cathode meet together, damage can be made for the battery.

7.2 Discharging current

The discharging current does not have to surpass this specification book stipulation the biggest discharging current, the oversized electric current electric discharge can cause the battery capacity play to reduce and to cause the battery heat.

7.3 Electric discharge temperature

The battery discharge must carry on in the ambient temperature scope which this specification book stipulated.

7.4 Over-discharges

Short time of excessively discharge will not affect the usage. But the long time excess discharge can damage the battery performance and cause the function losing. When the battery is not used for a long time, because of its automatic flashover characteristic, it may excessively discharges. To prevent excessively discharge occur, the battery should maintain certain electric quantity.

7.5 Storing the batteries

The battery should store in the product specification book stipulation temperature range. If has surpasses above for six months the long time storage, suggested you should carry on additional charge to the battery.

8 Other the chemical reaction

Because batteries utilize a chemical reaction, battery performance will deteriorate over time even if stored for a long period of time without being used. In addition, if the various usage conditions such as charge, discharge, ambient temperature, etc. are not maintained within the specified ranges the life expectancy of the battery may be shortened or the device in which the battery is used may be damaged by electrolyte leakage. If the batteries cannot maintain a charge for long periods of time, even when they are charged correctly, this may





436 Kato Terrace Fremont, CA 94539 Fax: 510.687.0328

Tel: 510.687.0388 Fax: 510.687.0328 www.Tenergy.com email: sales@tenergy.com

indicate it is time to change the battery.

9 Note

Any other items which are not covered in this specification shall be agreed by both parties.